


Powerful, versatile, cost-efficient

The VersiCharge AC series

Siemens VersiCharge chargers have stood for superior quality, ruggedness, and proven technology for more than a decade and have reliably provided millions of charges to EV (electric vehicle) drivers worldwide. The new third generation VersiCharge AC charger is continuing this tradition with numerous groundbreaking enhancements, a fresh and appealing design, and up to 11.5 kW of AC (alternating current) charging power. Providing various communication options, including the option to establish a parent-child configuration.

The VersiCharge AC charger can be connected to the customer's preferred back-end system making it scalable and cost-efficient. It also offers revenue-accurate metering and can interact with building management system, such as Siemens Desigo for dynamic load management that smartly adjusts as building energy demand changes. The rugged and slender VersiCharge AC charger is suitable for both indoor and outdoor use and can either be mounted on a wall or supplementary post.



The ideal solution for any application

Uniquely tailored for both commercial and home charging, VersiCharge AC charger comes with an easy-to-use mobile application and can charge any standard EV with just a tap of a button from your phone. VersiCharge AC home charger is energy star certified, and offers you cutting edge technology with the most affordable pricing.



VersiCharge AC Series – Technical data

Features and functions						
Charging mode	Level 2					
Vehicle connection	J1772 plug with 20 ft cable, 40/48 A / integrated cable management					
AC power output	Single phase up to 9.6 kW (40 A) or 11.5 kW (48 A)					
Mounting options	Wall and post mounting, see accessories					
Touch Button	Time delay, return to max power level, reset ground fault					
Charging status LEDs	Power, Cold start, time delay, charging state, reduced power level, authentication					
Communication status LEDs	Connected / not connected during operation, signal strength during commissioning					
Parent / child	Connect up to 10 child units by Wi-Fi (200 ft line of sight) and 24 child units by serial Modbus RS485. Each unit is provided with one Ethernet port.					
Load management	via OCPP or via Modbus					
Communication						
Interfaces	Ethernet, Wi-Fi, Modbus RS-485, Modbus TCP/IP, for parent units additionally LTE, WCDMA					
User authentification	RFID (local Whitelist, MiFare), ready for plug-and-charge acc. to ISO 15118 (upgradeable OTA)					
Configuration	via Siemens mobile app					
Back-end protocol	OCPP 1.6, upgrade-able to OCPP 2.0					
Software upgrade	over the air (OTA)					
Electrical design						
Power supply voltage	Single phase: 208 V / 240 V AC, 60 Hz					
Rated current settings (A)	12, 16, 24, 32, 40, 48					
Cross wire section	Single phase: 8 Awg / 6 Awg (75C rated wire)					
Network type	Single phase / split phase					
Energy metering	revenue accurate, ANSI C12.20 compliant metering					
Ground fault protection	20 mA					
DC residual current monitoring	Not applicable					
Over voltage protection	Under voltage: 167 V (min. 80 V) / over voltage: 267 V (max. 275 V)					
Over current protection	Current +10% above configured threshold, min. +2A, 5 seconds					
Operating altitude	9,840 ft					
General design						
Environmental rating	Indoor and Outdoor, NEMA 4, IK 10					
Dimensions (HxWxD)	40.9 x 18.1 x 9.6 (cm) / 16.10 x 7.09 x 3.78 (in)					
Weight	7.7 (kg) / 17 (lbs)					
Ambient conditions	Operating temperature: -35°C to 50°C (-31°F to 122°F), Storage Temp.: -40°C to 60°C (-40°F to 140°F), 98% non condensing					
Colours	Silver Metallic (Pantone 10077), Black holster					
Certificates and standards						
cUL listed	according to UL 1998, UL 991, UL2594/CSA C22.2 No.280/NMX-J-677-ANCE, UL 2231-1/CSA C22.2 No.281.1/NMX-J-668-1, UL 2231-2/CSA C22.2 No.281.2/NMX-J-668/2-ANCE, UL 2251/CSA C22.2 No.282/NMX-J-678-ANCE					

		Max. current	Model number	HW ready for ISO 15118	Wi-Fi and Ethernet		RFID identification		LTE WCDMA
Residential versions	Basic	40 A	8EM1312-4AF10-0AA3	_	_	_	_	_	_
		48 A	8EM1312-5AF10-0AA3						
	High End	40 A	8EM1312-4CF18-0FA3	~	~	_	_	~	-
		48 A	8EM1312-5CF18-0FA3						
Commercial versions	Child	40 A	8EM1310-4CF14-0GA0	~	~	~	~	~	-
		48 A	8EM1310-5CF14-0GA0						
	Parent	40 A	8EM1310-4CF14-1GA1	~	~	~	~	~	~
		48 A	8EM1310-5CF14-1GA1						