12 kW

## POWERPROTECT Standby Generators

DOWERPI

BRIGG





At nearly half the footprint of competitors, our 12kW<sup>1</sup> comes standard with **more power.** Its unique design and front-facing exhaust also allows for easy placement for installation outside your home.

# FEATURES



#### Warranty

6-Year limited warranty of parts, labor, and travel included for the entire term. The industry's most comprehensive warranty over time.<sup>2</sup>



#### **Compact Size**

30% smaller than competitive generators in its class<sup>3</sup> allows for a hassle-free installation.



# Assembled and Engineered in USA

Briggs & Stratton generators are designed and assembled in the USA.<sup>4</sup>



## **Flexible Placement Options**

Approved for installation as close as 18" to a building<sup>5</sup> with easy service access to the engine and alternator.



## Power Management System (optional)

Customizable to your home's power needs, Symphony<sup>®</sup> II and Amplify<sup>™</sup> Power Management systems offer prioritized whole house power with a more affordable standby generator.



## Commercial-Grade Vanguard<sup>®</sup> Engine

Powerful engine built in the USA for commercial applications providing power for electronics.



## Schaeffer<sup>®</sup> Full Synthetic Generator Oil Shields engine to reduce wear and tear and allows enhanced cold weather start-up protection to -20° F.



#### Quiet Weekly Test Mode

Over 75% quieter during weekly test mode.6



# POWERPROTECT

**Standby Generators** 

PP12
040666
12 / 10.8
50 / 45
120 / 240
60

Fuel Consumption <sup>7</sup>	
No Load (BTU/hr)	NG - 66,000 / LP - 57,000
Half Load (BTU/hr)	NG - 117,000 / LP - 155,000
Full Load (BTU/hr)	NG - 172,000 / LP - 209,000


BI	RIGG	S&STF	RATTO	N
			-	
all y			8	
				- 1


Engine	
Manufacturer	Vanguard®
Frequency Regulation Steady State	+/-1.0%

64 dBA
70 dBA

Available Accessories	
Battery Warmer	6578
Maintenance Kit	6873
Fuel Regulator Warmer	6845
Surge Protector	6631
Amplify Gateway	6520
UPS	6581
InfoHub™ Universal - Cellular	6574
Gateway Range Extender	6839

Product Dimensions	
Overall Dimensions (in / mm)	28 x 24.5 x 37.2 / 712 x 622 x 944
Packaged Dimensions (in / mm)	39 x 33.5 x 45 / 991 x 851 x 1143
Assembled Weight (lbs / kg)	361 / 164
Packaged Weight (lbs / kg)	423 / 192





<sup>1</sup> This generator is rated in accordance with UL (Underwriters Laboratories) 2200 (stationary engine generator assemblies) and CSA (Canadian Standards Association) standard C22.2 No. 100-14 (motor and generators).

<sup>2</sup> See operator's manual or BRIGGSandSTRATTON.com for complete warranty details.

<sup>3</sup> 30% smaller footprint than competitors.

<sup>4</sup> Of global and U.S. parts.

<sup>5</sup> The installation manual contains specific instructions related to generator placement in addition to NFPA 37, including the requirement that carbon monoxide detectors be installed and maintained in your home or business.

6 Compared to full load based on lowest microphone at 7 meters.

<sup>7</sup> Fuel consumption rates are estimated based on normal operating conditions. Generator operation may be greatly affected by elevation and the cycling operation of multiple electrical appliances – fuel flow rates may vary depending on these factors.

<sup>e</sup> Per ISO 3744. Sound level measurement at other locations around generator may differ depending on installation, based on lowest microphone at 7m. Normal operation based on average household usage.

Briggs & Stratton has a policy of continuous product improvement and reserves the right to modify its specifications at any time and without prior notice. This standby generator is not for Prime Power applications.

Published July 2021. Please visit BRIGGSandSTRATTON.com for the latest information. BS1303 - 7/21